1200300070

INTEGRA-07

PAVA Wall Mount System (7 amp channels pre installed)

- EN 54-16 CERTIFIED
- SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- SIMPLE INSTALLATION WITH MOUNTING FOR BATTERIES
- PRE-INSTALLED WITH 7 AMPLIFIER CHANNELS, EACH CAPABLE OF UP TO 500W @100V
- UP TO A TOTAL, 2000W @ 100V PER INTEGRA
- HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- 24 BIT 48 kHz AUDIO PROCESSING
- 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- FLEXIBLE CONTROL OPTIONS
- INTEROPERABILITY WITH THE VIPEDIA RANGE

Public Address Voice Alarm Commercial Audio Civil Defence Approval EN54 EN 54 Certified

Description

The Integra-07 Public Adress and Voice Alarm all-in-one network enabled voice alarm solution is available with seven channels of pre-installed amplification, which can be expanded at a later date.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With a maximum power of 2000W, integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure.

Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

Accessories

www.zenitel.com info@zenitel.com Last revision date: 2026-01-20 10:54

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

BMB01 from datasheet

BMB01

Din Rail Mount I/O Expansion Device

from site

D150

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA

from site

D500

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

Used With

VIPEDIA-12-NET

PAVA Audio router with network card

VIPEDIA-12-PRO

PAVA Audio router with network card - Dante Enabled

INTEGRA-PRO-03

PAVA Wall Mount System (3 amp channels pre installed) - Dante® Enabled

INTEGRA-PRO-05

PAVA Wall Mount System (5 amp channels pre installed) - Dante® Enabled

www.zenitel.com info@zenitel.com Last revision date: 2026-01-20 10:54

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

INTEGRA-PRO-07

PAVA Wall Mount System (7 amp channels pre installed) - Dante® Enabled

INTEGRA-PRO-10

PAVA Wall Mount System (10 amp channels pre installed) - Dante® Enabled

INTEGRA-03

Wall Mount PAVA System (3 amps)

INTEGRA-05

PAVA Wall Mount System (5 amp channels pre installed)

INTEGRA-07

PAVA Wall Mount System (7 amp channels pre installed)

INTEGRA-10

PAVA Wall Mount System (10 amp channels pre installed)

www.zenitel.com info@zenitel.com

Last revision date: 2026-01-20 10:54

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.